

# Load disconnect switches and motor starters



Safety switch

125 A / 160 A

8146/5-V37-608-00-0010 Art. No. 201401



- Large current range from 10 A to 180 A
- Can be used with conventional drives or with variable-frequency drives
- Intelligent design: A single rotary actuator for actuating the main and auxiliary contacts,  $\geq 20$  ms leading auxiliary contact for safe disconnection
- Designed in accordance with IEC/EN 62626-1, class 1
- The rotary actuator can be locked in the 0-position with three padlocks
- Cover can only be removed in the I-position

MY R. STAHL 8146L



R. STAHL Series 8146/5-V37 safety switches safely disconnect machines and system parts from the energy supply for cleaning and repair as prescribed. All of the installed load disconnect switches have AC-3 switching capacity. The switches can be locked in the 0-position using padlocks.

## Technical Data

### Explosion Protection

Area of application	European Union (ATEX) IECEX
Application range (zones)	1, 2, 21, 22
IECEX gas certificate	IECEX PTB 06.0090
IECEX gas explosion protection	Ex db eb IIC T6 / T4 Gb
IECEX dust certificate	IECEX PTB 06.0090
IECEX dust explosion protection	Ex tb IIIC T80 °C / T130 °C Db
ATEX gas certificate	PTB 01 ATEX 1024
ATEX gas explosion protection	⊕ II 2 G Ex db eb IIC T6 / T4 Gb
ATEX dust certificate	PTB 01 ATEX 1024
ATEX dust explosion protection	⊕ II 2 D Ex tb IIIC T80 °C / T130 °C Db
Certificates	ATEX (PTB), China (NEPSI), IECEX (PTB), India (PESO)
Declaration of conformity	ATEX (EUK), China (CCC)
Notes	Product label may vary. Series devices are labelled with ATEX and IECEX.

### Electrical Data

Rated operational voltage AC	690 V / 400 V
Rated operational current	125 A / 160 A
Switching capacity AC-3 230 V	37 kW / 45 kW
Switching capacity AC-3 400 V	55 kW / 90 kW
Switching capacity AC-3 440 V	75 kW / 90 kW
Switching capacity AC-3 500 V	75 kW / -- kW
Switching capacity AC-3 690 V	110 kW / -- kW
Auxiliary contact NC	without
Auxiliary contact NO	without
Frequency range	50 – 60 Hz

### Ambient Conditions

Note	You can find information about the ambient temperature online at <a href="http://r-stahl.com">r-stahl.com</a> . MY R. STAHL 8146L
------	---

# Load disconnect switches and motor starters



Safety switch

125 A / 160 A

8146/5-V37-608-00-0010 Art. No. 201401

## Ambient conditions

Ambient conditions	Number of poles		Max. current (A)	Conductor cross-section <sup>1)</sup> (mm <sup>2</sup> )		Temperature class/ perm. ambient temperature
	Main contacts	Auxiliary contacts		min.	max.	
	6	2	125	95	150	<b>T6: -40 to +40 °C</b> T5: -40 to +55 °C <sup>2)</sup> T4: -40 to +72 °C <sup>2)</sup>
			160	95	150	<b>T4: -40 to +40 °C</b> T4: -40 to +55 °C <sup>2)</sup>
			160	120	150	T4: -40 to +45 °C T4: -40 to +55 °C <sup>2)</sup>
<sup>1)</sup> Project engineering note: The maximum conductor cross-sections given were determined using the H07V. The minimum bending radius was assumed to be 4 x outer diameter in accordance with VDE 0298-3. <sup>2)</sup> Only with heat-resistant conductor > 70 °C at cable entries and/or > 85 °C at clamping units <b>Bold:</b> Information on the rating plate						

## Mechanical Data

Degree of protection (IP)	IP66
Degree of protection note	according to EN/IEC 60529
Enclosure material	Polyester resin, Glass fibre reinforced
Solid con. cross-section min.2	95 mm <sup>2</sup>
Min. fin.str. conn. cr.-sec. 2	95 mm <sup>2</sup>
Min. solid conn. cr.-sect. AWG	AWG 3/0
Min. solid con. cr.-sect. AWG2	AWG 3/0
Min. f.stra. con. cr.-sec. AWG	AWG 3/0
Min. f.str. con. cr.-sec. AWG2	AWG 3/0
Connection terminal auxiliary contact min. AWG	AWG 18
Connection cross section	95 ... 120 mm <sup>2</sup>
Auxiliary connection connection terminals	0.75 ... 2.5 mm <sup>2</sup>
Connection cross-section note	Depending on the application; for more detailed information, see the operating instructions at r-stahl.com
Construction type	Standard
Dimension A	1023 mm
Dimension A inch	40.28 in
Dimension B	681.5 mm
Dimension B inch	26.83 in
Dimension C	243 mm
Dimension C inch	9.57 in
Handle colour	Black shroud and handle
Seal	Silicone, foamed
Lockable in	Three times in 0 position
Detailed number of poles	6-pole
Weight	22.8 kg
Weight	50.18 lb

# Load disconnect switches and motor starters



## Safety switch


125 A / 160 A

8146/5-V37-608-00-0010 Art. No. 201401

### Components


Entry type	Standard 8161, moulded material
Cable gland	4 x M63 Ø 28 ... 48 mm 1 x M20 Ø 4 ... 13 mm

### Technical Drawings – Subject to Alterations



8146/5-V..6..00-.010  
6-pole

### Dimensional Drawings (All Dimensions in mm [inches]) – Subject to Alterations



### Accessories

#### Auxiliary contact



2 NC (8080/1-3)  
250 V AC/DC  
Max. 6 A  
1.5 to 2.5 mm<sup>2</sup>, solid/finely stranded  
The switching function of the auxiliary contact depends on the installation slot used.  
Left and right: Synchronising

Art. No.

168356

1 NC + 1 NO (8080/1-1)  
250 V AC/DC  
Max. 6 A  
1.5 to 2.5 mm<sup>2</sup>, solid/finely stranded  
The switching function of the auxiliary contact depends on the installation slot used.  
Left: Delayed (ON), leading (OFF)  
Right: Synchronising

168351

2 NO (8080/1-4)  
250 V AC/DC  
Max. 6 A  
1.5 to 2.5 mm<sup>2</sup>, solid/finely stranded  
The switching function of the auxiliary contact depends on the installation slot used.  
Left and right: Synchronising

168353

### Spare Parts

#### Auxiliary contact key



For removing installed auxiliary contacts

Art. No.

201909

# Load disconnect switches and motor starters



Safety switch

125 A / 160 A

8146/5-V37-608-00-0010 Art. No. 201401

---

We reserve the right to make alterations to the technical data, dimensions, weights, designs and products available without notice. The illustrations cannot be considered binding.